

FT-100 is the first fog machine from Antari specifically designed for fire training purpose.

Main Features:

- 1. Two rotary knobs and a LCD screen are equipped on FT-100. These allow users to set and control fog output volume and timer settings with ease, even when wearing heavy-duty gloves.
- 2. A 1500 Watt heater block is capable of generating high volume thick fog in short time to simulate dense fog at fires.
- 3. W-2 wireless remote controller included.
- 4. The red paint finish gives FT-100 the identity of being part of fire industry.

- Voltage : U.S. version : 120 Volt Europe version: 230 Volt U.K. version: 240 Volt

Japan version: 100 Volt

- Breaker: AC-120V, 15A/250V AC-230V, 7A/250V

- Power Consumption: 1,500W - Output : 20000 cu.ft / min - Initial Heat-Up Time: 10 mins

- Fluid Consumption Rate: 100 ml/ min

- Tank Capacity: 6 liters

- Remote Included: W-2 Wireless Remote

- Control Options : Z-3 Remote

- Weight: 14.2 Kg

- Dimensions (mm) : L 580 x W 278.2 x H 264.5

- Liquid Used : Antari FLP Fog Liquid





■ FT-100 Effects



 Timer / Volume Control Knobs



Real Panel



 W-2 Wireless Remote Wontroller Included.



Antari FLP Fog Liquid

